



2SK1740

N-Channel Junction Silicon FET

HF Amplifiers Low-Frequency Amplifiers Analog Switches

Features

- Adoption of FBET process.
- Large $|y_{fs}|$.
- Small Ciss
- Small-sized package permitting 2SK1740-applied sets to be made small and slim.

Specifications

Absolute Maximum Ratings at $T_a=25^\circ\text{C}$

Parameter	Symbol	Conditions	Ratings	Unit
Drain-to-Source Voltage	V_{DSX}		40	V
Gate-to-Drain Voltage	V_{GDS}		-40	V
Gate Current	I_G		10	mA
Drain Current	I_D		75	mA
Allowable Power Dissipation	P_D		250	mW
Junction Temperature	T_J		150	$^\circ\text{C}$
Storage Temperature	T_{stg}		-55 to +150	$^\circ\text{C}$

Electrical Characteristics at $T_a=25^\circ\text{C}$

Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	
Gate-to-Drain Breakdown Voltage	$V_{(BR)GDS}$	$I_G=-10\mu\text{A}$, $V_{DS}=0\text{V}$	-40			V
Gate-to-Source Leakage Current	I_{GSS}	$V_{GS}=-20\text{V}$, $V_{DS}=0\text{V}$			-1.0	nA
Cutoff Voltage	$V_{GS(off)}$	$V_{DS}=10\text{V}$, $I_D=100\mu\text{A}$	-2.0	-3.0	-5.0	V
Drain Current	I_{DSS}	$V_{DS}=10\text{V}$, $V_{GS}=0\text{V}$	40*		75*	mA
Forward Transfer Admittance	$ y_{fs} _1$	$V_{DS}=10\text{V}$, $I_D=10\text{mA}$, $f=1\text{kHz}$	10	15		mS
	$ y_{fs} _2$	$V_{DS}=10\text{V}$, $V_{GS}=0\text{V}$, $f=1\text{kHz}$	22	30		mS
Input Capacitance	Ciss	$V_{DS}=10\text{V}$, $V_{GS}=0\text{V}$, $f=1\text{MHz}$			11	pF
Reverse Transfer Capacitance	Crss	$V_{DS}=10\text{V}$, $V_{GS}=0\text{V}$, $f=1\text{MHz}$			2.5	pF
Noise Figure	NF	$V_{DS}=10\text{V}$, $R_g=1\text{k}\Omega$, $I_D=1\text{mA}$, $f=1\text{kHz}$			1.5	dB
Static Drain-to-Source On-State Resistance	$R_{DS(on)}$	$I_D=10\text{mA}$, $V_{GS}=0\text{V}$			30	Ω

Marking : IJ

* : Pulse Test Pulse Width \leq 2ms.

* : The 2SK1740 is classified by I_{DSS} as follows : (unit : mA).

Rank	3	4	5
I_{DSS}	40 to 52	48 to 63	57 to 75






■ Any and all SANYO Semiconductor products described or contained herein do not have specifications that can handle applications that require extremely high levels of reliability, such as life-support systems, aircraft's control systems, or other applications whose failure can be reasonably expected to result in serious physical and/or material damage. Consult with your SANYO Semiconductor representative nearest you before using any SANYO Semiconductor products described or contained herein in such applications.

■ SANYO Semiconductor assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all SANYO Semiconductor products described or contained herein.


Package Dimensions









unit : mm (typ)





7013A-011



2SK1740







- Specifications of any and all SANYO Semiconductor products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.
- SANYO Semiconductor Co., Ltd. strives to supply high-quality high-reliability products. However, any and all semiconductor products fail with some probability. It is possible that these probabilistic failures could give rise to accidents or events that could endanger human lives, that could give rise to smoke or fire, or that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.
- In the event that any or all SANYO Semiconductor products (including technical data, services) described or contained herein are controlled under any of applicable local export control laws and regulations, such products must not be exported without obtaining the export license from the authorities concerned in accordance with the above law.
- No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of SANYO Semiconductor Co., Ltd.
- Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the SANYO Semiconductor product that you intend to use.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO Semiconductor believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.

This catalog provides information as of October, 2006. Specifications and information herein are subject to change without notice.